#### Part No:

# HA65A-03





The HASCO Fixed Attenuator **HA65A-03** is rated to 1 Watts and operates from DC to 65GHz. The versatile coaxial package uses 1.85mm male to 1.85mm female connectors.

The HA65A-03 is RoHS compliant.



RF microwave attenuators (also known as RF pads) lower the amplitude of a signal (attenuate) a known amount and can be used in a wide variety of applications. These attenuator pads are used when a signal needs to be reduced to protect measurement equipment or other circuitry, to extend the range of power meters and amplifiers, and to impedance match circuits by reducing the VSWR seen by adjacent components. RF attenuators can prevent signal overload in amplifiers, receivers and detectors, adjusting the signal level to a range that is optimal.

## *3 dB - Fixed Attenuator 1.85mm Male To 1.85mm Female Up To 65 GHz Rated To 1 Watt With Passivated Stainless Steel Body*

### **Electrical**

					/
Frequency Range	DC - 65 GHz				
Attenuation Accuracy 1-9 dB	<u>DC-26.5 GHz</u> ± 0.75 dB	26.5-40 GHz ± 1.00 dB	40-50 GHz ±1.50 dB	<u>50-65 GHz</u> ±1.50 dB	
10 dB 20 dB 30 dB	± 0.75 dB ±1.00 dB ±1.25 dB	± 1.25 dB ±1.25 dB ±1.50 dB	±1.50 dB ±2.00 dB ±2.00 dB	±1.75 dB ±2.50 dB ±5.50 dB	
• VSWR • Impedence	1.35:1 50 Ohms	1.55:1	1.55:1	1.65:1	
• Power	1 Watt Averag Derates linearly				

### Environmental Data

• Temperature Range -55°C - +100°C

#### Material

Dielectric High Temperature Plastic Bead
Contact Beryllium Copper

Gold Plated IAW MIL-PRF-39012

- Housing Passivated Stainless Steel IAW
  - ASTM-A484 & ASTM-A582, Alloy 303 Cond A
- Conductor

To view online, go to: https://www.hasco-inc.com/attenuators/3-db-fixed-attenuator-1-85mm-male-to-1-85mm-female-up-to-65-ghz-rated-to-1-watt-with-passivated-stainless-steel-body/

5214 Bonsai Street • Moorpark, CA 93021 (888) 498-3242 • sales@hasco-inc.com www.hasco-inc.com

