

Part No:

# 24J-35P-FM



## *2.4mm Female to 3.5mm Male Adapter • DC- 33GHz*



The HASCO **24J-35M-FM** is an Adapter that operates from DC to 33 GHz and handles up to 1,000 cycles. Our 2.4mm to 3.5mm Between-Series Adapters offer 1.15:1 max VSWR.

HASCO stocks an extensive selection of RF and Microwave Between-series adapters and In-series coaxial adapters. Precision In-Series adapters include: SMA adapters, 3.5mm adapters, 2.92mm adapters, 2.40mm adapters, and 1.85mm adapters. Some of the Between-Series adapters available are Type N to SMA, SMA to 2.40mm, 3.5mm to 2.92mm, 2.92mm to 2.40mm, SSMA, to 2.92mm, SSMA to 2.4mm.

### Electrical

• Frequency Range	DC - 33 GHz
• VSWR	DC - 33 GHz..... 1.15 MAX
• Impedence	50 Ohms
• Durability	1,000 Cycles

### Environmental Data

• Temperature Range	-65°C - +165°C
---------------------	----------------

### Material

• Dielectric	PEI, Natural
• Center Conductor	Gold Plated Beryllium Copper
• Body	Passivated Stainless Steel

To view online, go to: <https://www.hasco-inc.com/adapters/2-4mm-female-to-3-5mm-male-adapter-33-ghz-hasco-components/>