

Part No:

24P-35J-MF



HASCO, INC
COMPONENTS DISTRIBUTOR



2.4mm Male to 3.5mm Female Adapter • DC- 33Hz

Electrical

- Frequency Range DC - 33 GHz
- VSWR DC - 33 GHz..... 1.15 MAX
- Impedance 50 Ohms
- Durability 1,000 Cycles

Environmental Data

- Temperature Range -65°C - +165°C

Material

- Dielectric PEI, Natural
- Center Conductor Gold Plated Beryllium Copper
- Body Passivated Stainless Steel

The HASCO **24P-35J-MF** is an Adapter that operates from DC to 33 GHz and handles up to 1,000 cycles. Our 2.4mm to 3.5mm Between-Series Adapters offer 1.15:1 max VSWR.

HASCO stocks an extensive selection of RF and Microwave Between-series adapters and In-series coaxial adapters. Precision In-Series adapters include: SMA adapters, 3.5mm adapters, 2.92mm adapters, 2.40mm adapters, and 1.85mm adapters. Some of the Between-Series adapters available are Type N to SMA, SMA to 2.40mm, 3.5mm to 2.92mm, 2.92mm to 2.40mm, SSMA, to 2.92mm, SSMA to 2.4mm.

To view online, go to: <https://www.hasco-inc.com/adapters/2-4mm-male-to-3-5mm-female-adapter-33-ghz-hasco-components/>