Part No: **HT18M-67**



The HASCO **HT18M-67** is an RF termination (also called RF load or dummy load) that operates from DC to 67 GHz and handles up to 1 Watt (CW). Our 1.85mm termination/load has a Male gender. **HT18M-67** termination offers 1.4:1 max VSWR DC-67GHz.

The HT18M-67 is RoHS Compliant.



RF load/terminations are indispensable components in many RF, microwave and millimeter wave systems where signal reflection from unused ports can potentially damage the device or reduce the signal integrity. By using a termination on an unused port with a matched load (dummy load), the incident energy will be absorbed with minimal reflection. These termination components are commonly used to terminate devices such as couplers, circulators, and switches. They are also widely used in measurement systems to ensure accurate results. HASCO offers a huge selection of RF, microwave and millimeter wave terminations up to 65 GHz with excellent performance over the entire operating range and power handling capabilities up to 800 Watt (CW).

1 Watt RF Load Termination with 1.85mm Male Connector DC-67 GHz

Electrical

Electrical	
Frequency Range	DC - 67 GHz
• VSWR	DC - 67 GHz 1.4:1
Impedence	50Ω
• Power	1 Watt Average (-40°C to 70°C Linearly Derated to 0.7 Watt at 105°C)
Insertion Loss	≤0.05 x √f(GHz) dB
Insulation Resistance	≥5000MΩ
Dielectric Withstanding Voltage	500V rms (sea level)
Working Voltage	150V rms (sea level)
• RF Leakage	≥100dB to 1GHz
Environmental Data	
Temperature Range	-55°C - +105°C
Material	
• Body	Passivated Stainless Steel
• Contact Pin	Beryllium Copper (Plating: Gold 4 Over Nickel-Phosphorus Alloy 80, Over Copper 20)
• Insulator	PPO
Back Cover	Aluminium
Retainer Ring	Beryllium Copper (Plating: Tin-Zinc-Copper-Alloy 100, Over Copper 50)
• Gasket	Silicone
Coupling Nut	Passivated Stainless Steel

HASCO, INC

