




HASCO
COMPONENTS

888-498-3242
www.hasco-inc.com



Scan or Click to
[View and Download](#)
[HASCO Catalog Pages](#)









LAUNCH ACCESSORIES

HASCO provides an extensive selection of Hermetic Seals, Feed Thrus and Launch Pins from Southwest Microwave and HASCO, Inc.

The end launch accessories are designed to interface with Southwest Microwave's and other manufacturer's end launch connectors that use common end launch .005 pin, .007 pin, .009 pin, .010 pin, .012 pin, .015 pin, .020 pin, .0290 pin, .0390 pin, .0480 pin and .0635 pin connectors.

To view all Southwest Microwave connectors, launch accessories and test boards, please visit HASCO's website at www.hasco-inc.com

FEEDTHRUS/HERMETIC SEALS

PHOTO	PART #	PIN A	BODY LTH	PIN B	BODY DIA	PIN DIA	OP FREQ	GLASS
	HA-V01	0.026 ±0.005	0.055 ±0.002	0.031 ±0.005	0.068 ±0.002	0.009 ±0.001	65 GHz	CORNING 7070
	HA-V100/ V100B	0.025 ±0.003	0.055 ±0.002	0.032 ±0.003	0.068 ±0.001	0.009 ±0.001	65 GHz	CORNING 7070
	HA-3180	0.031 ±0.005	0.055 ±0.002	0.0180 ±0.005	0.068 ±0.001	0.009 ±0.001	65 GHz	CORNING 7070
	HA-089	0.072 ±0.007	0.0625 ±0.0025	0.180 ±0.0010	0.099 ±0.0015	0.012 ±0.001	42 GHz	CORNING 7052
	HA-095	0.040 ±0.005	0.055 ±0.002	0.080 ±0.005	0.076 ±0.002	0.012 ±0.005	42 GHz	CORNING 7070
	HA-1361	0.040 ±0.005	0.055 ±0.002	0.125 ±0.003	0.076 ±0.002	0.012 ±0.001	42 GHz	CORNING 7070
	HA-1869	0.055 0.005	0.069 ±0.002	0.180 ±0.001	0.076 ±0.001	0.012 ±0.001	42 GHz	CORNING 7070
	HA-2940	0.029 ±0.005	0.055 ±0.002	0.041 ±0.005	0.076 ±0.002	0.012 ±0.001	42 GHz	CORNING 7070
	HA-4040	0.040 ±0.005	0.055 ±0.002	0.040 ±0.005	0.076 ±0.002	0.012 ±0.001	42 GHz	CORNING 7070
	HA-074	0.050 ±0.005	0.062 ±0.002	0.125 ±0.005	0.098 ±0.002	0.015 ±0.001	28 GHz	CORNING 7070
	HA-075	0.060 ±0.005	0.062 ±0.002	0.190 ±0.005	0.098 ±0.002	0.015 ±0.001	28 GHz	CORNING 7070
	HA-079	0.072 ±0.007	0.060 ±0.002	0.018 ±0.010	0.110 ±0.002	0.018 ±0.001	18 GHz	CORNING 7070
	HA-459	0.072 ±0.005	0.060 ±0.002	0.250 ±0.010	0.110 ±0.015	0.018 ±0.001	18 GHz	CORNING 7070
	HA-1071	0.180 ±0.007	0.060 ±0.002	0.180 ±0.007	0.110 ±0.002	0.018 ±0.005	18 GHz	CORNING 7070
	HA-1397-06	0.100 ±0.005	0.060 ±0.002	0.250 ±0.005	0.110 ±0.002	0.018 ±0.001	18 GHz	CORNING 7070
	HA-247	0.100 ±0.005	0.060 ±0.002	0.600 ±0.002	0.110 ±0.002	0.018 ±0.001	18 GHz	CORNING 7070
	HA-084	0.095 ±0.005	0.060 ±0.002	0.125	0.158	0.020 ±0.001	8 GHz	CORNING 7052
	HA-184	0.095 ±0.005	0.060 ±0.002	0.500 ±0.005	0.158 ±0.0015	0.020 ±0.005	8 GHz	CORNING 7052